

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025
© Flex

Key Features

- Ultra-wide input voltage range 10:1
- Case dimensions
62.0*40.0*13.0 mm (2.44*1.57*0.51 inch)
- High Efficiency up to 89%
- 4000 Vdc input to output isolation
- Meets safety requirements according to IEC/EN/UL 62368-1
- Compliant with EN50155
- EN45545-2 compliant
- Hold Up (BUS pin with external Caps)
- UVLO Set up (UVLO pin, resistor programmable)



General Characteristics

- Input under voltage shutdown
- Remote control
- Output over voltage protection
- Over temperature protection
- Output short-circuit protection
- Output voltage adjust function
- ISO 9001/14001 certified supplier

Safety Approvals



Design for Environment



Meets requirements in high-temperature lead-free soldering processes.

Contents

Ordering Information	2
General Information	2
Safety Specification	3
Absolute Maximum Ratings	4
Electrical Specification	
12 V, 12.5 A / 150 W	PKM7213WPI 5
24 V, 6.25 A / 150 W	PKM7216ZWPI 9
54 V, 2.78 A / 150 W	PKM7216HWPI 13
EMC Specification	17
Operating Information	19
Thermal Consideration	21
Connections	23
Mechanical Information	24
Soldering Information	26
Delivery Information	26
Product Qualification Specification	27

Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025

© Flex

Ordering Information

Product program	Output
PKM7213WPI	12V, 12.5A / 150W
PKM7216ZWPI	24V, 6.25A / 150W
PKM7216HWPI	54V, 2.78A / 150W

Product number and Packaging

PKM72XXXWPI _{n1}	
Options	n ₁
Remote Control logic	o

Options	Description
n ₁	Negative* P Positive

Example: a 54 V output product with positive logic, tray packaging would be PKM72116HWPI.

* Standard variant (i.e. no option selected).

General Information

Reliability

The failure rate (λ) and mean time between failures (MTBF = $1/\lambda$) is calculated at max output power and an operating ambient temperature (T_A) of +40°C. Flex uses Telcordia SR-332 Issue 3 Method 1 to calculate the mean steady-state failure rate and standard deviation (σ).

Telcordia SR-332 Issue 3 also provides techniques to estimate the upper confidence levels of failure rates based on the mean and standard deviation.

Mean steady-state failure rate, λ	Std. deviation, σ
667.54072 nFailures/h	297.07277 nFailures/h

MTBF (mean value) for the PKM7200W series = 1.5 Mh.
MTBF at 90% confidence level = 0.94 Mh

Compatibility with RoHS requirements

The products are compatible with the relevant clauses and requirements of the RoHS directive 2011/65/EU and have a maximum concentration value of 0.1% by weight in homogeneous materials for lead, mercury, hexavalent chromium, PBB and PBDE and of 0.01% by weight in homogeneous materials for cadmium.

Exemptions in the RoHS directive utilized in Flex products are found in the Statement of Compliance document.

Flex fulfills and will continuously fulfill all its obligations under regulation (EC) No 1907/2006 concerning the registration, evaluation, authorization and restriction of chemicals (REACH) as they enter into force and is through product materials declarations preparing for the obligations to communicate information on substances in the products.

Quality Statement

The products are designed and manufactured in an industrial environment where quality systems and methods like ISO 9000, Six Sigma, and SPC are intensively in use to boost the continuous improvements strategy. Infant mortality or early failures in the products are screened out and they are subjected to an ATE-based final test. Conservative design rules, design reviews and product qualifications, plus the high competence of an engaged work force, contribute to the high quality of the products.

Warranty

Warranty period and conditions are defined in Flex General Terms and Conditions of Sale.

Limitation of Liability

Flex does not make any other warranties, expressed or implied including any warranty of merchantability or fitness for a particular purpose (including, but not limited to, use in life support applications, where malfunctions of product can cause injury to a person's health or life).

© Flex 2025

The information and specifications in this technical specification is believed to be correct at the time of publication. However, no liability is accepted for inaccuracies, printing errors or for any consequences thereof. Flex reserves the right to change the contents of this technical specification at any time without prior notice.

Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025

© Flex

Safety Specification

General information

Flex Power DC/DC converters and DC/DC regulators are designed in accordance with the safety standards IEC 62368-1, EN 62368-1 and UL 62368-1 *Audio/video, information and communication technology equipment - Part 1: Safety requirements*

IEC/EN/UL 62368-1 contains requirements to prevent injury or damage due to the following hazards:

- Electrical shock
- Electrically-caused fire
- Injury caused by hazardous substances
- Mechanically-caused injury
- Skin burn
- Radiation-caused injury

On-board DC/DC converters, Power interface modules and DC/DC regulators are defined as component power supplies. As components they cannot fully comply with the provisions of any safety requirements without "conditions of acceptability". Clearance between conductors and between conductive parts of the component power supply and conductors on the board in the final product must meet the applicable safety requirements. Certain conditions of acceptability apply for component power supplies with limited stand-off (see Mechanical Information for further information). It is the responsibility of the installer to ensure that the final product housing these components complies with the requirements of all applicable safety standards and regulations for the final product.

Component power supplies for general use shall comply with the requirements in IEC/EN/UL 62368-1. Product related standards, e.g. IEEE 802.3af *Power over Ethernet*, and ETS-300132-2 *Power interface at the input to telecom equipment, operated by direct current (dc)* are based on IEC/EN/UL 62368-1 with regards to safety.

Flex Power DC/DC converters, Power interface modules and DC/DC regulators are UL 62368-1 recognized and certified in accordance with EN 62368-1. The flammability rating for all construction parts of the products meet requirements for V-0 class material according to IEC 60695-11-10, *Fire hazard testing, test flames – 50 W* horizontal and vertical flame test methods.

Isolated DC/DC converters & Power interface modules

The product may provide basic or functional insulation between input and output according to IEC/EN/UL 62368-1 (see Safety Certificate), different conditions shall be met if the output of a basic or a functional insulated product shall be considered as ES1 energy source.

For basic insulated products (see Safety Certificate) the output is considered as ES1 energy source if one of the

following conditions is met:

- The input source provides supplementary or double or reinforced insulation from the AC mains according to IEC/EN/UL 62368-1.
- The input source provides functional or basic insulation from the AC mains and the product's output is reliably connected to protective earth according to IEC/EN/UL 62368-1.

For functional insulated products (see Safety Certificate) the output is considered as ES1 energy source if one of the following conditions is met:

- The input source provides double or reinforced insulation from the AC mains according to IEC/EN/UL 62368-1.
- The input source provides basic or supplementary insulation from the AC mains and the product's output is reliably connected to protective earth according to IEC/EN/UL 62368-1.
- The input source is reliably connected to protective earth and provides basic or supplementary insulation according to IEC/EN/UL 62368-1.

Galvanic isolation between input and output is verified in an electric strength test and the isolation voltage (V_{iso}) meets the voltage strength requirement for basic insulation according to IEC/EN/UL 62368-1.

It is recommended to use a slow blow fuse at the input of each DC/DC converter. If an input filter is used in the circuit the fuse should be placed in front of the input filter. In the rare event of a component problem that imposes a short circuit on the input source, this fuse will provide the following functions:

- Isolate the fault from the input power source so as not to affect the operation of other parts of the system
- Protect the distribution wiring from excessive current and power loss thus preventing hazardous overheating

Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C


March 2025

© Flex

Absolute Maximum Ratings

Characteristics			min	typ	max	Unit
T _{P1}	Operating Temperature (see Thermal Consideration section)		-40		+100	°C
T _S	Storage temperature		-55		+110	°C
V _I	Input voltage		16	72	160	V
V _{iso}	Isolation voltage (Input to Output)				4000	Vdc
V _{iso}	Isolation voltage (Input to Baseplate)				2250	Vdc
V _{iso}	Isolation voltage (Baseplate to Output)				1500	Vdc
V _{tr}	Input voltage transient (tp 1s)				185	V
V _{RC}	Remote Control pin voltage (see Operating Information section)	Positive logic option	0		5	V
		Negative logic option	0		5	V

Stresses above those listed under Absolute Maximum Ratings may cause permanent damage to the device. This is a stress rating only; functional operation of the device at these or any other conditions above those indicated in the Electrical Specification section of this specification is not implied. Exposure to absolute maximum rating conditions for extended periods may affect device reliability.

Fundamental Circuit Diagram For PKM7213WPI(P), PKM7216JWPI(P), PKM7216HWPI(P)

Technical Specification

PKM7200W series DC-DC Converters
 Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025

© Flex

Electrical Specification
12V, 12.5 A / 150 W
PKM72113WPI(P)
 $T_{P1} = -40$ to $+90^{\circ}\text{C}$, $V_I = 16$ to 160 V, sense pins connected to output pins unless otherwise specified under Conditions.

 Typical values given at: $T_{P1} = +25^{\circ}\text{C}$, $V_I = 72$ V, I_O max I_O , unless otherwise specified under Conditions.

 The input external capacitor is recommended to be in parallel with 220 $\mu\text{F}/200$ V E-Cap to reduce input ripple and stabilize input voltage.

 At least 220 $\mu\text{F}/200$ V E-Cap is added in the converter BUS pin. External capacitor needs to be close to the converter.

 At least 1500 μF E-Cap is added in the converter output for stabilizing output voltage. External capacitor needs to be close to the converter.

Characteristics	Conditions	min	typ	max	Unit
V_I	Input voltage range	16		160	V
V_{Ioff}	Turn-off input voltage	Decreasing input voltage		13.5	V
V_{Ion}	Turn-on input voltage	Increasing input voltage		16	V
C_I	Internal input capacitance		4.7		μF
P_O	Output power	0		150	W
η	Efficiency	50% of max I_O	-		%
		max I_O	-		
		50% of max I_O , $V_I = 72$ V	88.5		
		max I_O , $V_I = 72$ V	88.0		
P_d	Power Dissipation	max I_O	15.75		W
P_{ii}	Input idling power	$I_O = 0$ A, $V_I = 72$ V	2		W
P_{RC}	Input standby power	$V_I = 72$ V (turned off with RC)	0.7		W
f_s	Switching frequency	0-100 % of max I_O	210		kHz

V_{Oi}	Output voltage initial setting and accuracy	$T_{P1} = +25^{\circ}\text{C}$, $V_I = 72$ V, $I_O = 12.5$ A	11.88	12	12.12	V
V_O	Output adjust range	See operating information	6.0		13.2	V
	Output voltage tolerance band	0-100% of max I_O	11.88	12	12.12	V
	Idling voltage	$I_O = 0$ A	11.88	12	12.12	V
	Line regulation	max I_O			± 120	mV
	Load regulation	$V_I = 72$ V, 25-100% of max I_O			± 120	mV
V_{tr}	Load transient voltage deviation	$V_I = 72$ V, Load step 50-75-50% of max I_O , $di/dt = 100$ mA/ μs		± 500		mV
t_{tr}	Load transient recovery time				500	μs
t_r	Ramp-up time (from 10–90% of V_{Oi})	10-100% of max I_O , $T_{P1} = 25^{\circ}\text{C}$, $V_I = 72$ V		22.42		ms
t_s	Start-up time (from V_I connection to 90% of V_{Oi})			30.3		ms
t_{RC}	RC start-up time (from V_{RC} connection to 90% of V_{Oi})	max I_O		21.5		ms
RC	Sink current	See operating information	0.5			mA
	Trigger level	Decreasing / Increasing RC-voltage		0.8/2.5		V
t_f	V_I shut-down fall time (from V_I off to 10% of V_O)	max I_O		450		μs
		$I_O = 0$ A		9.5		ms
I_O	Output current		0		12.5	A
I_{lim}	Current limit threshold	$T_{P1} < \max T_{P1}$	13.0		20.0	A
I_{sc}	Short circuit current	$T_{P1} = 25^{\circ}\text{C}$, see Note 1		250		mA
C_{out}	Recommended Capacitive Load	$T_{P1} = 25^{\circ}\text{C}$	0		3000	μF
V_{Oac}	Output ripple & noise	See ripple & noise section, V_{Oi} , max I_O , see Note 2		100	150	mVp-p
OVP	Over voltage protection	$T_{P1} = +25^{\circ}\text{C}$, $V_I = 72$ V, 0-100% of max I_O	13.5		18	V

Note 1: RMS current at OCP in hiccup mode.

Note 2: Measured by 20 MHz bandwidth with a 1 μF ceramic cap and a 47 $\mu\text{F}/20$ V POS-CAP

Technical Specification


PKM7200W series DC-DC Converters
 Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C


March 2025

© Flex


Typical Characteristics
12V, 12.5 A / 150 W

PKM7213WPI(P)**Efficiency**


Efficiency vs. load current and input voltage at +25°C.

Power Dissipation

Dissipated power vs. load current and input voltage at +25°C.

Output Current Derating

Available load current vs. ambient air temperature and airflow at $V_i = 72$ V. See Thermal Consideration section.

Current Limit Characteristics

Output voltage vs. load current at $I_o > \max I_o$ at +25°C.

Technical Specification


PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C


March 2025

© Flex


Typical Characteristics
12V, 12.5 A / 150 W

PKM7213WPI(P)**Output Current Derating**

Available load current vs. ambient air temperature and airflow at $V_I = 72\text{ V}$ with 20 mm $\frac{1}{4}$ brick heat sink. See Thermal Consideration section.

Output Current Derating – Cold wall sealed box

Available load current vs. cold wall temperature.
 $V_I = 110\text{ V}$.

Output Power Derating

Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C

March 2025

© Flex

Typical Characteristics

12V, 12.5 A / 150 W

PKM7213WPI(P)

Start-up

Start-up enabled by connecting V_i at: $T_{P1} = +25^\circ\text{C}$, $V_i = 72\text{ V}$, $I_o = 12.5\text{ A}$ resistive load.

Top trace: output voltage (5 V/div.).

Bottom trace: input voltage (50 V/div.).

Time scale: (50 ms/div.).

Shut-down


Shut-down enabled by disconnecting V_i at: $T_{P1} = +25^\circ\text{C}$, $V_i = 72\text{ V}$, $I_o = 12.5\text{ A}$ resistive load.

Top trace: output voltage (5 V/div.).

Bottom trace: input voltage (50 V/div.).

Time scale: (2 ms/div.).

Output Ripple & Noise



Output voltage ripple at:


 $T_{P1} = +25^\circ\text{C}$, $V_i = 72\text{ V}$, $I_o = 12.5\text{ A}$ resistive load.

Trace: output voltage (50 mV/div.).

Time scale: (10 μs/div.).

20 MHz bandwidth.

Output Load Transient Response



Output voltage response to load current step-change (6.25-9.375-6.25 A) at:

 $T_{P1} = +25^\circ\text{C}$, $V_i = 72\text{ V}$.

Top trace: output voltage (50 mV/div.).

Bottom trace: load current (2 A/div.).

Time scale: (500 μs/div.).

Output Voltage Adjust (TRIM UP/TRIM DOWN)

Output Voltage = 12 V

The resistor value for an adjusted output voltage is calculated by using the following equations:

Output Voltage Adjust, Increase:

$$R_{\text{TRIM_UP}} = \left(\frac{5.11 \times V_{o,\text{set}} \times (100 + \Delta\%)}{1.225 \times \Delta\%} - \frac{511}{\Delta\%} - 10.22 \right) \text{ k}\Omega$$

$$\Delta\% = \left(\frac{V_{\text{desired}} - V_{o,\text{set}}}{V_{o,\text{set}}} \right) \times 100$$

Output Voltage Adjust, Decrease:

$$R_{\text{TRIM_DOWN}} = \left(\frac{511}{\Delta\%} - 10.22 \right) \text{ k}\Omega$$

$$\Delta\% = \left(\frac{V_{o,\text{set}} - V_{\text{desired}}}{V_{o,\text{set}}} \right) \times 100$$

Example:

To trim up the 12.0 V model by 8% to 12.96 V the required external resistor is:

$$R_{\text{TRIM_UP}} = \left(\frac{5.11 \times 12 \times (100 + 8)}{1.225 \times 8} - \frac{511}{8} - 10.22 \right) = 601.68 \text{ k}\Omega$$

$$\Delta\% = \left(\frac{12.96 - 12}{12} \right) \times 100 = 8$$

Example:

To trim down the 12.0 V model by 7% to 11.16 V the required external resistor is:

$$R_{\text{TRIM_DOWN}} = \left(\frac{511}{7} - 10.22 \right) = 62.78 \text{ k}\Omega$$

Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025

© Flex

Electrical Specification
24 V, 6.25 A / 150 W
PKM7216ZWPI(P)

$T_{P1} = -40$ to $+90^{\circ}\text{C}$, $V_I = 16$ to 160 V, sense pins connected to output pins unless otherwise specified under Conditions.

Typical values given at: $T_{P1} = +25^{\circ}\text{C}$, $V_I = 72$ V, I_O max I_O , unless otherwise specified under Conditions.

The input external capacitor is recommended to be in parallel with $220\text{ }\mu\text{F}/200$ V E-Cap to reduce input ripple and stabilize input voltage.

At least $220\text{ }\mu\text{F}/200$ V E-Cap is added in the converter BUS pin. External capacitor needs to be close to the converter.

At least $680\text{ }\mu\text{F}$ E-Cap is added in the converter output for stabilizing output voltage. External capacitor needs to be close to the converter.

Characteristics	Conditions	min	typ	max	Unit
V_I	Input voltage range	16		160	V
V_{Ioff}	Turn-off input voltage	Decreasing input voltage	11.5	13.5	V
V_{Ion}	Turn-on input voltage	Increasing input voltage	14	16	V
C_I	Internal input capacitance		4.7		μF
P_O	Output power	0		150	W
η	Efficiency	50% of max I_O	-		%
		max I_O	-		
		50% of max I_O , $V_I = 72$ V	88.5		
		max I_O , $V_I = 72$ V	89.0		
P_d	Power Dissipation	max I_O	15.75		W
P_{ii}	Input idling power	$I_O = 0$ A, $V_I = 72$ V	2		W
P_{RC}	Input standby power	$V_I = 72$ V (turned off with RC)	0.7		W
f_s	Switching frequency	0-100 % of max I_O	210		kHz

V_{Oi}	Output voltage initial setting and accuracy	$T_{P1} = +25^{\circ}\text{C}$, $V_I = 72$ V, $I_O = 6.25$ A	23.76	24	24.24	V
V_O	Output adjust range	See operating information	12.0		26.4	V
	Output voltage tolerance band	0-100% of max I_O	23.76	24	24.24	V
	Idling voltage	$I_O = 0$ A	23.76	24	24.24	V
	Line regulation	max I_O			± 240	mV
	Load regulation	$V_I = 72$ V, 25-100% of max I_O			± 240	mV
V_{tr}	Load transient voltage deviation	$V_I = 72$ V, Load step 50-75-50% of max I_O , $di/dt = 100$ mA/ μs		± 500		mV
t_{tr}	Load transient recovery time			500		μs
t_r	Ramp-up time (from 10-90% of V_{Oi})	10-100% of max I_O , $T_{P1} = 25^{\circ}\text{C}$, $V_I = 72$ V		45.0		ms
t_s	Start-up time (from V_I connection to 90% of V_{Oi})			87.0		ms
t_{RC}	RC start-up time (from V_{RC} connection to 90% of V_{Oi})	max I_O		90.0		ms
RC	Sink current	See operating information	0.5			mA
	Trigger level	Decreasing / Increasing RC-voltage		0.8/2.5		V
t_f	V_I shut-down fall time (from V_I off to 10% of V_O)	max I_O		12		ms
		$I_O = 0$ A		8.0		s
I_O	Output current		0		6.25	A
I_{lim}	Current limit threshold	$T_{P1} < \max T_{P1}$	6.5		11.0	A
I_{sc}	Short circuit current	$T_{P1} = 25^{\circ}\text{C}$, see Note 1		80		mA
C_{out}	Recommended Capacitive Load	$T_{P1} = 25^{\circ}\text{C}$	0		2000	μF
V_{Oac}	Output ripple & noise	See ripple & noise section, V_{Oi} , max I_O , see Note 2		100	150	mVp-p
OVP	Over voltage protection	$T_{P1} = +25^{\circ}\text{C}$, $V_I = 72$ V, 0-100% of max I_O	25.6		30	V

Note 1: RMS current at OCP in hiccup mode.

Note 2: Measured by 20 MHz bandwidth with a $1\text{ }\mu\text{F}$ ceramic cap and a $47\text{ }\mu\text{F}/35$ V POS-CAP

Technical Specification





PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C

March 2025

© Flex

Typical Characteristics
24 V, 6.25 A / 150 W

PKM7216ZWPI(P)**Efficiency****Power Dissipation****Output Current Derating****Current Limit Characteristics**

Technical Specification


PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C


March 2025

© Flex


Typical Characteristics
24V, 6.25 A / 150 W

PKM7216ZWPI(P)**Output Current Derating**

Available load current vs. ambient air temperature and airflow at $V_i = 72\text{ V}$ with 20 mm $\frac{1}{4}$ brick heat sink. See Thermal Consideration section.

Output Current Derating – Cold wall sealed box

Available load current vs. cold wall temperature.
 $V_i = 110\text{ V}$.

Output Power Derating

Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C


March 2025

© Flex


Typical Characteristics
24 V, 6.25 A / 50 W

PKM7216ZWPI(P)


Start-up




Shut-down



Output Ripple & Noise



Output Load Transient Response



Output Voltage Adjust (TRIM UP/TRIM DOWN)

Output Voltage = 24 V

The resistor value for an adjusted output voltage is calculated by using the following equations:

Output Voltage Adjust, Increase:

$$R_{\text{TRIM_UP}} = \left(\frac{5.11 \times V_{o,\text{set}} \times (100 + \Delta\%)}{1.225 \times \Delta\%} - \frac{511}{\Delta\%} - 10.22 \right) \text{ k}\Omega$$

$$\Delta\% = \left(\frac{V_{\text{desired}} - V_{o,\text{set}}}{V_{o,\text{set}}} \right) \times 100$$

Output Voltage Adjust, Decrease:

$$R_{\text{TRIM_DOWN}} = \left(\frac{511}{\Delta\%} - 10.22 \right) \text{ k}\Omega$$

$$\Delta\% = \left(\frac{V_{o,\text{set}} - V_{\text{desired}}}{V_{o,\text{set}}} \right) \times 100$$

Example:

To trim up the 24 V model by 8% to 25.92 V the required external resistor is:

$$R_{\text{TRIM_UP}} = \left(\frac{5.11 \times 24 \times (100 + 8)}{1.225 \times 8} - \frac{511}{8} - 10.22 \right) = 1277.45 \text{ k}\Omega$$

$$\Delta\% = \left(\frac{25.92 - 24}{24} \right) \times 100 = 8$$

Example:

To trim down the 24 V model by 7% to 22.32 V the required external resistor is:

$$R_{\text{TRIM_DOWN}} = \left(\frac{511}{7} - 10.22 \right) = 62.78 \text{ k}\Omega$$

Technical Specification

PKM7200W series DC-DC Converters
 Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025

© Flex

Electrical Specification
54 V, 2.78 A / 150 W
PKM7216HWPI(P)
 $T_{P1} = -40$ to $+90^{\circ}\text{C}$, $V_I = 16$ to 160 V, sense pins connected to output pins unless otherwise specified under Conditions.

 Typical values given at: $T_{P1} = +25^{\circ}\text{C}$, $V_I = 72$ V, I_O max I_O , unless otherwise specified under Conditions.

 The input external capacitor is recommended to be in parallel with 220 μF /200 V E-Cap to reduce input ripple and stabilize input voltage.

 At least 220 μF /200V E-Cap is added in the converter BUS pin. External capacitor needs to be close to the converter.

 At least 390 μF E-Cap is added in the converter output for stabilizing output voltage. External capacitor needs to be close to the converter.

Characteristics	Conditions	min	typ	max	Unit
V_I	Input voltage range	16		160	V
V_{Ioff}	Turn-off input voltage	Decreasing input voltage	11.5	13.5	V
V_{Ion}	Turn-on input voltage	Increasing input voltage	14	16	V
C_I	Internal input capacitance		4.7		μF
P_O	Output power	0		150	W
η	Efficiency	50% of max I_O	-		%
		max I_O	-		
		50% of max I_O , $V_I = 72$ V	88.5		
		max I_O , $V_I = 72$ V	89.0		
P_d	Power Dissipation	max I_O	15.75		W
P_{ii}	Input idling power	$I_O = 0$ A, $V_I = 72$ V	2		W
P_{RC}	Input standby power	$V_I = 72$ V (turned off with RC)	0.7		W
f_s	Switching frequency	0-100 % of max I_O	240		kHz

V_{Oi}	Output voltage initial setting and accuracy	$T_{P1} = +25^{\circ}\text{C}$, $V_I = 72$ V, $I_O = 2.78$ A	54.54	54	54.54	V
V_O	Output adjust range	See operating information	27.0		59.4	V
	Output voltage tolerance band	0-100% of max I_O	53.46	54	54.54	V
	Idling voltage	$I_O = 0$ A	53.46	54	54.54	V
	Line regulation	max I_O			± 540	mV
	Load regulation	$V_I = 72$ V, 25-100% of max I_O			± 540	mV
V_{tr}	Load transient voltage deviation	$V_I = 72$ V, Load step 50-75-50% of max I_O , $di/dt = 100$ mA/ μs		± 500		mV
t_{tr}	Load transient recovery time			500		μs
t_r	Ramp-up time (from 10-90% of V_{Oi})	10-100% of max I_O , $T_{P1} = 25^{\circ}\text{C}$, $V_I = 72$ V		11.635		ms
t_s	Start-up time (from V_I connection to 90% of V_{Oi})			32.0		ms
t_{RC}	RC start-up time (from V_{RC} connection to 90% of V_{Oi})	max I_O		26.0		ms
RC	Sink current	See operating information	0.5			mA
	Trigger level	Decreasing / Increasing RC-voltage		0.8/2.5		V
t_f	V_I shut-down fall time (from V_I off to 10% of V_O)	max I_O		8.5		ms
		$I_O = 0$ A		3.5		s
I_O	Output current		0		2.78	A
I_{lim}	Current limit threshold	$T_{P1} < \max T_{P1}$	3.0		5.0	A
I_{sc}	Short circuit current	$T_{P1} = 25^{\circ}\text{C}$, see Note 1		310		mA
C_{out}	Recommended Capacitive Load	$T_{P1} = 25^{\circ}\text{C}$	0		150	μF
V_{Oac}	Output ripple & noise	See ripple & noise section, V_{Oi} , max I_O , see Note 2			400	mVp-p
OVP	Over voltage protection	$T_{P1} = +25^{\circ}\text{C}$, $V_I = 72$ V, 0-100% of max I_O	59.4		72	V

Note 1: RMS current at OCP in hiccup mode.

Note 2: Measured by 20 MHz bandwidth with a 1 μF ceramic cap and a 100 μF /63V PSC-CAP

Technical Specification





PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C

March 2025

© Flex

Typical Characteristics
54 V, 2.78 A / 150 W

PKM7216HWPI(P)**Efficiency****Power Dissipation****Output Current Derating****Current Limit Characteristics**

Technical Specification


PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C


March 2025

© Flex


Typical Characteristics
54 V, 2.78 A / 150 W

PKM7216HWPI(P)**Output Current Derating**

Available load current vs. ambient air temperature and airflow at $V_I = 72$ V with 20 mm $\frac{1}{4}$ brick heat sink. See Thermal Consideration section.

Output Current Derating – Cold wall sealed box

Available load current vs. cold wall temperature.
 $V_I = 110$ V.

Output Power Derating

Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C

March 2025


© Flex

Typical Characteristics

54 V, 2.78 A / 150 W

PKM7216HWPI(P)

Start-up


Start-up enabled by connecting V_i at:

$T_{P1} = +25^\circ\text{C}$, $V_i = 72\text{ V}$,
 $I_o = 2.78\text{ A}$ resistive load.

Top trace: output voltage (20 V/div.).

Bottom trace: input voltage (50 V/div.).
Time scale: (10 ms/div.).

Shut-down


Shut-down enabled by disconnecting V_i at:

$T_{P1} = +25^\circ\text{C}$, $V_i = 72\text{ V}$,
 $I_o = 2.78\text{ A}$ resistive load.

Top trace: output voltage (20 V/div.).

Bottom trace: input voltage (50 V/div.).
Time scale: (5 ms/div.).

Output Ripple & Noise




Output voltage ripple at:

$T_{P1} = +25^\circ\text{C}$, $V_i = 72\text{ V}$,
 $I_o = 2.78\text{ A}$ resistive load.

Trace: output voltage (100 mV/div.).

Time scale: (5 μs/div.).
20 MHz bandwidth.

Output Load Transient Response



Output voltage response to load current step-
change (1.39-2.085-1.39 A) at:
 $T_{P1} = +25^\circ\text{C}$, $V_i = 72\text{ V}$.

Top trace: output voltage (50 mV/div.).

Bottom trace: load current (0.5 A/div.).
Time scale: (500 μs/div.).

Output Voltage Adjust (TRIM UP/TRIM DOWN)

The resistor value for an adjusted output voltage is calculated by using the following equations:

Output Voltage Adjust, Increase:

$$R_{\text{TRIM_UP}} = \left(\frac{5.11 \times V_{o,\text{set}} \times (100 + \Delta\%)}{1.225 \times \Delta\%} - \frac{511}{\Delta\%} - 10.22 \right) \text{ k}\Omega$$

$$\Delta\% = \left(\frac{V_{\text{desired}} - V_{o,\text{set}}}{V_{o,\text{set}}} \right) \times 100$$

Output Voltage Adjust, Decrease:

$$R_{\text{TRIM_DOWN}} = \left(\frac{511}{\Delta\%} - 10.22 \right) \text{ k}\Omega$$

$$\Delta\% = \left(\frac{V_{o,\text{set}} - V_{\text{desired}}}{V_{o,\text{set}}} \right) \times 100$$

Output Voltage = 54 V

Example:

To trim up the 54 V model by 8% to 58.32 V the required external resistor is:

$$R_{\text{TRIM_UP}} = \left(\frac{5.11 \times 54 \times (100 + 8)}{1.225 \times 8} - \frac{511}{8} - 10.22 \right) = 2966.88 \text{ k}\Omega$$

$$\Delta\% = \left(\frac{58.32 - 54}{54} \right) \times 100 = 8$$

Example:

To trim down the 54 V model by 7% to 50.22 V the required external resistor is:

$$R_{\text{TRIM_DOWN}} = \left(\frac{511}{7} - 10.22 \right) = 62.78 \text{ k}\Omega$$

Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C


March 2025

© Flex

EMC Specification

Conducted EMI measured according to EN55032, CISPR 32 and FCC part 15J (see test set-up). See Design Note 009 for further information. The fundamental switching frequency is 200 kHz for PKM7200W series at $V_I = 72$ V and max I_O .


Conducted EMI Input terminal value (typ)



EMI without filter

Optional external filter for class B

Suggested external input filter in order to meet class B in EN 55032, CISPR 32 and FCC part 15J.



PKM7200W Filter components:


C1, C4 = 220 μ F C2 = 100 μ F C6 = 470 μ F (EE-Cap)

CY1, CY2 = 2.2 μ F (Y-Cap)


C01 = 2.2 μ F (MLCC)

L01 = 8.0 mH L02 = 1.0 μ H (CM Choke)

NC: CY3, CY4, CY5, CY6, C5, C7 are for fine tuning when necessary



EMI with filter



Test set-up

Layout recommendations

The radiated EMI performance of the product will depend on the PWB layout and ground layer design. It is also important to consider the stand-off of the product. If a ground layer is used, it should be connected to the output of the product and the equipment ground or chassis.

A ground layer will increase the stray capacitance in the PWB and improve the high frequency EMC performance.

Technical Specification


PKM7200W series DC-DC Converters Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025
© Flex

Output ripple and noise

Output ripple and noise measured according to figure below.
See Design Note 022 for detailed information.


- PKM7213WPI(P) and PKM7216ZWPI(P):



Output ripple and noise test setup

	PART NO.	VENDOR
Polymer capacitor	T523W476M035APE100	KEMET
Ceramic capacitor	SSM21X105K100T	S.S.E

- PKM7216HWAPI(P):



Output ripple and noise test setup

	PART NO.	VENDOR
Polymer capacitor	HHSD630ELL101MJC5S	NIPPON Chemi-Con
Ceramic capacitor	SSM21X105K100T	S.S.E

Technical Specification

PKM7200W series DC-DC Converters
 Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025

© Flex

Operating Information**Input Voltage**


The input voltage range 16 to 160 Vdc meets the requirements of world-wide railway systems, at input voltages exceeding 160 V, the power loss will be higher than at normal input voltage and T_{P1} must be limited to absolute max +100°C. The absolute maximum continuous input voltage is 160 Vdc.

Short duration transient disturbances can occur on the DC distribution and input of the product when a short circuit fault occurs on the equipment side of a protective device (fuse or circuit breaker). The voltage level, duration and energy of the disturbance are dependant on the particular DC distribution network characteristics and can be sufficient to damage the product unless measures are taken to suppress or absorb this energy. The transient voltage can be limited by capacitors and other energy absorbing devices like zener diodes connected across the positive and negative input conductors at a number of strategic points in the distribution network. The end-user must secure that the transient voltage will not exceed the value stated in the Absolute maximum ratings. ETSI TR 100 283 examines the parameters of DC distribution networks and provides guidelines for controlling the transient and reduce its harmful effect.

Turn-off Input Voltage

The products monitor the input voltage and will turn on and turn off at predetermined levels.

The minimum hysteresis between turn on and turn off input voltage is 1.7 V.

Remote Control (RC)

The products are fitted with a remote control function referenced to the primary negative input connection (-In), with negative and positive logic options available. The RC function allows the product to be turned on/off by an external device like a semiconductor or mechanical switch. The RC pin has an internal pull up resistor to +5 V.

The external device must provide a minimum required sink current to guarantee a voltage not higher than maximum voltage on the RC pin (see Electrical characteristics table). When the RC pin is left open, the voltage generated on the RC pin is 3 - 5 V.

The standard product is provided with "negative logic" RC and will be off until the RC pin is connected to the -In. To turn off the product the RC pin should be left open, or connected to a voltage higher than 2 V referenced to -In. In situations where it is desired to have the product to power up automatically without the need for control signals or a switch, the RC pin can be wired directly to -In.

The second option is "positive logic" remote control, which can be ordered by adding the suffix "P" to the end of the part number. When the RC pin is left open, the product starts up automatically when the input voltage is applied. Turn off is achieved by connecting the RC pin to the -In. The product will restart automatically when this connection is opened.

See Design Note 021 for detailed information.

Input and Output Impedance

The impedance of both the input source and the load will interact with the impedance of the product. It is important that the input source has low characteristic impedance. The products are designed for stable operation with a minimum of 220 μ F external capacitors connected to the input. The electrolytic capacitors will be degraded in low temperature and the ESR value may increase. The needed input capacitance in low temperature should be equivalent to 220 μ F at 20° C. This means that the input capacitor value may need to be substantially larger to guarantee a stable input at low temperatures. The performance in some applications can be enhanced by addition of external capacitance as described under External Decoupling Capacitors. The minimum required capacitance value depends on the output power and the input voltage. The higher output power the higher input capacitance is needed.

External Decoupling Capacitors

When powering loads with significant dynamic current requirements, the voltage regulation at the point of load can be improved by addition of decoupling capacitors at the load. The most effective technique is to locate low ESR ceramic and electrolytic capacitors as close to the load as possible, using several parallel capacitors to lower the effective ESR. The ceramic capacitors will handle high-frequency dynamic load changes while the electrolytic capacitors are used to handle low frequency dynamic load changes. It is equally important to use low resistance and low inductance PWB layouts and cabling.

External decoupling capacitors will become part of the product's control loop. The control loop is optimized for a wide range of external capacitance and the maximum recommended value that could be used without any additional analysis is found in the Electrical specification.

The ESR of the capacitors is a very important parameter. Stable operation is guaranteed with a verified ESR value of >5 m Ω across the output connections.

For further information please contact your local Ericsson Power Modules representative.

Technical Specification

PKM7200W series DC-DC Converters
 Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025

© Flex

Output Voltage Adjust (V_{adj})

The products have an Output Voltage Adjust pin (V_{adj}). This pin can be used to adjust the output voltage above or below Output voltage initial setting.

When increasing the output voltage, the voltage at the output pins (including any remote sense compensation) must be kept below the threshold of the over voltage protection, (OVP) to prevent the product from shutting down. At increased output voltages the maximum power rating of the product remains the same, and the max output current must be decreased correspondingly.

To increase the voltage the resistor should be connected between the V_{adj} pin and +Sense pin. The resistor value of the Output voltage adjust function is according to information given under the Output section for the respective product.

To decrease the output voltage, the resistor should be connected between the V_{adj} pin and -Sense pin.


resume normal operation automatically when the temperature has dropped $>10^{\circ}\text{C}$ below the temperature threshold.

Over Voltage Protection (OVP)

The products have output over voltage protection that will shut down the product in over voltage conditions. The product will make continuous attempts to start up (non-latching mode) and resume normal operation automatically after removal of the over voltage condition.

Over Current Protection (OCP)

The products include current limiting circuitry for protection at continuous overload. The output voltage will decrease towards zero for output currents in excess of max output current (max I_o). The product will resume normal operation after removal of the overload. The load distribution should be designed for the maximum output short circuit current specified.

**Parallel Operation**

Two products may be paralleled for redundancy if the total power is equal or less than P_o max. It is not recommended to parallel the products without using external current sharing circuits.

See Design Note 006 for detailed information.

Remote Sense

The products have remote sense that can be used to compensate for voltage drops between the output and the point of load. The sense traces should be located close to the PWB ground layer to reduce noise susceptibility. The remote sense circuitry will compensate for up to 10% voltage drop between output pins and the point of load.

If the remote sense is not needed +Sense should be connected to +Out and -Sense should be connected to -Out.

Over Temperature Protection (OTP)

The products are protected from thermal overload by an internal over temperature shutdown circuit.

When T_{P1} as defined in thermal consideration section exceeds 115°C the product will shut down. The product will make continuous attempts to start up (non-latching mode) and

Technical Specification

PKM7200W series DC-DC Converters
 Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C

March 2025

© Flex


Thermal Consideration

General


The products are designed to operate in different thermal environments and sufficient cooling must be provided to ensure reliable operation.

For products mounted on a PWB without a heat sink attached, cooling is achieved mainly by conduction, from the pins to the host board, and convection, which is dependant on the airflow across the product. Increased airflow enhances the cooling of the product. The Output Current Derating graph found in the Output section for each model provides the available output current vs. ambient air temperature and air velocity at $V_I = 72V$.


The product is tested on a 254 x 254 mm, 35 μm (1 oz), 8-layer test board mounted vertically in a wind tunnel with a cross-section of 608 x 203 mm.



For products with base plate used in a sealed box/cold wall application, cooling is achieved mainly by conduction through the cold wall. The Output Current Derating graphs are found in the Output section for each model. The product is tested in a sealed box test set up with ambient temperatures 85, 55 and 25°C. See Design Note 028 for further details.



Base plate



Technical Specification

PKM7200W series DC-DC Converters
 Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C March 2025


© Flex

The Hold-up time Circuit

Hold up time is defined as the duration of time that DC/DC converter output will remain active following a loss of input power. To meet power supply interruptions, voltage bleeding resistors and reverse polarity protection diodes should be included to provide a discharge path for the capacitors, avoiding injury from stored charge, and protecting the capacitors from damage at turn-on and turn-off.

The BUS pin is for hold-up time function. It is designed to work with an external circuit comprising C_{hold}, R, D. When input power supply is interrupted, the PKM7200W series use the energy stored in C_{hold} to support operation.

An external circuit is required, shown below.



The Hold-up time Circuit components:

- D: 200 V/10 A
- R: 100 Ω /10 W
- C_{in}, C1: 220 μ F/200 V ESR < 0.7 Ω

- ◇ The capacitance of C_{in} keeps the input voltage stable.
- ◇ The capacitance of C1 should always be installed and connected to the BUS pin for the module's stability. (External capacitor C1 need to close to the converter)
- ◇ The capacitance of C_{hold} decides the hold-up time during interruption of input power. When choosing a hold-up time capacitor C_{hold}, it is recommended to use capacitors with low Equivalent Series Resistance (ESR) as well as high rated for high ripple current. (When higher voltage is involved, it will be likely necessary to use two or more capacitors in series and/or series-parallel configurations to achieve the required total capacitance)
- ◇ Connected resistor (R) and diode (D) in series with the capacitor input side, the inrush current can be alleviated.
 - The resistor (R) is used to limit in-rush current during hold-up capacitor charging.
 - The capacitor (C_{hold}) can feed the power back to the DC bus through diode (D).

- ◇ The relationship for PKM7213WP(I) and PKM7216ZWPI(P) is shown in the table below.

Hold-Up time	24 V _I	36 V _I	48 V _I	72 V _I	96 V _I	110 V _I
10 ms	1800 μF				550 μF	330 μF
20 ms	3600 μF				1100 μF	660 μF
30 ms	5400 μF				1650 μF	990 μF
V _{BUS}	80 V				96 V	110 V
V _{rate of c1}	>= 100 V				>= 160 V	


- ◇ The relationship for PKM7216HWPI(P) is shown in the table below.

Hold-Up time	24 V _I	36 V _I	48 V _I	72 V _I	96 V _I	110 V _I
10 ms	2700 μF				1600 μF	800 μF
20 ms	3600 μF				3200 μF	1600 μF
30 ms	5400 μF				4800 μF	2400 μF
V _{BUS}	90 V				96 V	110 V
V _{rate of c1}	>= 100 V				>= 160 V	

UVLO (Under Voltage Lock Out)

UVLO Pin is for adjust turn on/off threshold voltage between +Vin and -Vin by connecting a resistor between UVLO PIN and -Vin.

Under normal start-up conditions, converters will not begin to regulate properly until the rising input voltage exceeds and remains at the Start-Up Threshold Voltage. Once operating, converters will not turn off until the input voltage drops below the Under-Voltage Shutdown Limit. Subsequent restart will not occur until the input voltage rises again above the Start-Up Threshold. This built-in hysteresis prevents any unstable on/off operation at a single input voltage. An external circuit is required, shown below.



The UVLO circuit components:

- C_{in}, C1: 220 μ F/200 V ESR < 0.7 Ω
- R_{adj} is shown in the table below

The table shown as below to obtain the suitable R_{adj} value to the system.


Nominal Vin	24 V _I	36 V _I	48 V _I	72 V _I	96 V _I	110 V _I
Turn-off Threshold	12.0 \pm 1V	17.1 \pm 1V	25.8 \pm 1V	39.5 \pm 2V	57.7 \pm 2V	62 \pm 2V
Turn-on threshold	15.0 \pm 1V	20.0 \pm 1V	28.5 \pm 1V	42.2 \pm 2V	60.4 \pm 2V	66.5 \pm 2V
UVLO External Resistor	open	32.6K	12.1K	6.0K	3.6K	3.3K

Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C	March 2025
© Flex	

Connections



Pin Connections	
Pin	Function
1	+Vin
2	UVLO
3	Remote On/Off Control
4	BUS
5	-Vin
6	-Vout
7	-Vsense
8	Trim
9	+Vsense
10	+Vout

Technical Specification


PKM7200W series DC-DC Converters
 Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C

March 2025

© Flex

Mechanical Information - Enclosure Type



Notes:

1.Pins:

Material: Brass

Plating: Nickel

2.Weight: typical 70g

All dimensions in inches (mm).

Tolerance .xx= ± 0.04 ".xxx= ± 0.010 "

Technical Specification


PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C

March 2025

© Flex

RECOMMEND PWB LAYOUT



Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C

March 2025

© Flex

Soldering Information - Hole Mounting


The hole mounted product is intended for plated through hole mounting by wave or manual soldering. The pin temperature is specified to maximum to 270°C for maximum 10 seconds.

A maximum preheat rate of 4°C/s and maximum preheat temperature of 150°C is suggested. When soldering by hand, care should be taken to avoid direct contact between the hot soldering iron tip and the pins for more than a few seconds in order to prevent overheating.


A no-clean flux is recommended to avoid entrapment of cleaning fluids in cavities inside the product or between the product and the host board. The cleaning residues may affect long time reliability and isolation voltage.

Delivery Package Information

The products are delivered in antistatic clamshell trays

A. Package**Tray Specifications**

Material	Antistatic PS
Surface resistance	$10^5 < \text{Ohm/square} < 10^{11}$
Bakeability	This tray is not bakeable
Tray thickness	21.0 mm [0.82677 inch]
Box capacity	96 products (8 full trays/box)
Tray weight	85 g empty, 817 g full tray



Technical Specification

PKM7200W series DC-DC Converters
Input 16-160 V, Output up to 12.5 A / 150 W

28701-BMR7157200 Rev C

March 2025

© Flex

Product Qualification Specification

Characteristics			
External visual inspection	IPC-A-610		
Change of temperature (Temperature cycling)	IEC 60068-2-14 Na	Temperature range Number of cycles Dwell/transfer time	-55 to 105°C 20 30 min/3 min
Cold (in operation)	IEC 60068-2-1 Ad	Temperature T _A Duration	-45°C 72 h
Damp heat	IEC 60068-2-30	Temperature Humidity Duration	45°C 95 % RH 72 hours
Dry heat	IEC 60068-2-2 Bd	Temperature Duration	125°C 1000 h
Electrostatic discharge susceptibility	IEC 61340-3-1, JESD 22-A114	Human body model (HBM)	Class 2, 2000 V
Mechanical shock	IEC 60068-2-27 Ea	Peak acceleration Duration	200 g 6 ms
Moisture reflow sensitivity ¹	J-STD-020E	Level 1 (SnPb-eutectic) Level 3 (Pb Free)	225°C 260°C
Operational life test	MIL-STD-202G, method 108A	Duration	1000 h
Resistance to soldering heat	IEC 60068-2-20 Tb, method 1A	Solder temperature Duration	270°C 10-13 s
Robustness of terminations	IEC 60068-2-21 Test Ua1	Through hole mount products	All leads
Solderability	IEC 60068-2-20 test Ta ¹	Preconditioning Temperature, SnPb Eutectic Temperature, Pb-free	235°C 245°C
Vibration, broad band random	IEC 60068-2-64 Fh, method 1	Frequency RMS acceleration Duration	10 to 500 Hz 0.07 g ² /Hz 10 min in each direction

Notes

¹ Only for products intended for wave soldering (plated through hole products)

EN 50155		
Phenomenon	EN50155 Reference Clause(s)	Reference Standard
Characteristic Test	12.2.1, 12.2.2, 5.1.1.1, 5.1.3, 12.2.9, 12.2.6	-
EMC	12.2.7, 12.2.8	EN 50121-3-2 EN 61000-4 EN 55011
Environmental Tests	12.2.3, 12.2.4, 12.2.5, 12.2.11	EN 60068-2 EN 61373